

What's in the Box?

PART NO.	QTY	DESCRIPTION
V2V-AV2H-01	1	SVideo, Composite Video and Audio to HDMI Converter
PS5VDC2A	1	5 Volt 2 Amp Power Supply

Technical Specifications

COMPOSITE VIDEO	
Input Format	NTSC/PAL/SECAM
Output Formats	NTSC/PAL/SECAM
Resolution	800 x 600, 1024 x 768, up to 1280 x 1024@60Hz
Input Interface	(3) RCA Female
S-VIDEO	
Input Format	NTSC/PAL/SECAM
Resolution	800 x 600, 1024 x 768, up to 1280 x 1024@60Hz
Input Interface	(1) S-Video Female
HDMI VIDEO	
Format	HDMI 1.3b [Deep Color, xvYcc color space supported]
DVI Compliance	Single-link DVI-D 1.1
HDCP Compliance	1.0/1.1
Video Bandwidth	Single-link 340MHz [10.2Gbps]
Resolution	480i,480p,720i,720p,1080i,1080p
Output Interface	(1) HDMI[7.1ch audio & video]
Connector	Type A[19-pin female]
Maximum Distance	25 ft.
AUDIO	
Signal Type	Stereo Unbalanced
Output Interface	Left/Right RCA (Female)
OTHER	
Power	External 100-240 VAC/5VDC2A @10W
Dimensions	5.25 in W x 3.5 in H x 1 in D
Weight	0.71 lb
Operating Temp.	0-55 °C (32-131°F)
Storage Temp.	-20-85 °C (-4-185 °F)
Humidity	Up to 95%

© Copyright 2012 SmartAVI, All Rights Reserved

NOTICE

The information contained in this document is subject to change without notice. Smart-AVI makes no warranty of any kind with regard to this material, including but not limited to, implied warranties of merchantability and fitness for any particular purpose.

Smart-AVI will not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance or use of this material.

No part of this document may be photocopied, reproduced or translated into another language without prior written consent from Smart-AVI.

For more information, visit www.smartavi.com.

Rack Mountable Option



Our SmartRack is the perfect solution to allow virtually all SmartAVI devices to be custom mounted in a standard 19" server rack. The SmartRack is fully adjustable and can secure/organize several devices.

Smart-AVI
SMART AUDIO VIDEO INNOVATION

SmartAVI, Inc. / Twitter: smartavi
11651 Vanowen St. North Hollywood, CA 91605
Tel: (818) 503-6200 Fax: (818) 503-6208
<http://www.SmartAVI.com>

Smart-AVI
SMART AUDIO VIDEO INNOVATION

V2V FAMILY

Installation Manual

V2V-AV2H-01



S-Video and Composite to HDMI Converter



www.smartavi.com

Introduction

The V2V-AV2H-01 Converts S-Video or Composite Video and Stereo Audio to HDMI.


Features

- One S-Video Signal Input
- One AV Signal Input
- R/L Audio Signal Input
- One HDMI Signal Output
- HDMI Signal 720p/60HZ Output
- Adaptive PAL / NTSC standard
- LED Indicators
- Easy to install within minutes

Applications

- Home Theater
- PC Networking
- Conference Center Systems
- Point of Sale
- Camera Surveillance
- Video Phone
- Control Room Systems
- Recording Studios

Product - Installation Diagram



Installation

1. Connect a composite or S-Video input device.
2. Connect an HDMI display to the HDMI output on the V2V-AV2H-01.
3. Connect the power cord to the V2V-AV2H-01.
4. Power on the input device and the display.

Button Function

Use the front panel button to switch between Composite and S-Video, indicated by the LEDs.

V2V-C2V-01 Front



V2V-C2V-01 Rear

